

## PCS 1900 MHz Duplex Filter

Data: 28.05.2010

**PCS1900DPF** duplex filter allows bi-directional communication over a single channel. It isolates the receiver from the transmitter while permitting them to share a common antenna.

### Key features:

- Low passband insertion loss
- High stopband attenuation
- Compact case
- Wide operating temperature range

### Applications:

- Test-and Measurement Systems
- Micro/Pico Base stations
- Repeaters
- Boosters



### Specifications

Characteristic	Uplink	Downlink
Frequency range	1850 -1910MHz	1930 -1990MHz
Bandwidth	60MHz	60MHz
Passband Insertion Loss	<3.5dB	<3.5dB
Passband ripple	<1.5dB	<1.5dB
Passband Return Loss	>12dB	>12dB
Stopband attenuation	>40dB@1930 -1990MHz	>40dB@1850 - 1910MHz
RF power		5W max.
RF connectors		3xSMAf
Case dimensions		57x40x17mm
Operating temperature		-40...+85°C

